Micro-Power Boost DC/DC Converter

Features

Operating Voltage : 2.7V ~ 5.5VHigh Operating Frequency : 1MHz

■ Shutdown Current : <1µA■ High Output Voltage : Up to 40V

■ Soft Start Function

■ Cycle by Cycle Current Limiting

■ SOT-23-5 Package

Applications

- STN/OLED BIAS
- Personal Digital Assistants
- DSC
- TV Tunner

General Description

The G5135 boost converter contains a 0.7Ω internal switch. The IC operates at constant frequency 1MHz, allowing the use of tiny, low cost and low height inductors and capacitors. The IC operates from a 2.7V to 5.5V supply voltage and can boost supply voltage up to 40V at the output. High inrush current at start-up is eliminated using the soft-start function. Constant frequency current mode PWM architecture results in low, predictable output noise. The G5135 includes cycle-by-cycle 850mA current limiting to maximum inductor current and over-temperature protection circuit. The G5135 is suitable for small or medium size LCD panel of high bias voltage with a constant current to provide PDAs, and other portable devices. The G5135 is available in SOT-23-5 package.

Ordering Information

ORDER NUMBER	MARKING	TEMP. RANGE	PACKAGE (Pb free)
G5135T11U	5135x	-40°C to 85°C	SOT-23-5

Note: T1: SOT-23-5 1: Bonding Code U: Tape & Reel

Pin Configuration

Typical Application Circuit



